

November 28, 1996

---

## **SyQuest EZ135 Parallel Port Driver with Windows 95**

---

If you are having a problem with accessing your A:\ drive after installing a SyQuest EZ135 Parallel Port drive for use with Windows 95, you need to manually change a driver to resolve the problem. The following steps will walk you through the procedure to resolve this issue.

1. Copy the EPATHD.MDP driver from this archive (W95135A.EXE) to your c:\windows\system\iosubsys directory. This will replace the existing driver with the newer driver.
2. Hold down the ALT key and double-click on the "My Computer" icon.
3. The Systems Properties Window appears.
4. Double-click on the SCSI Controllers entry.
5. Double-click on the SyQuest Parallel Port Device entry.  
The SyQuest Parallel Port Device Properties Window appears.
6. Click on the Settings Tab.
7. In the Adapter Settings area enter /SP (a forward slash followed by the letters S and P).
8. Click on the OK button.
9. Click on the OK button again.
10. Click on the Start button.
11. Click on Shutdown..... The Shutdown Window appears.
12. Select the Restart the Computer? radio button.
13. Click on the Yes button.
14. When you return to the Windows desktop, your A:\ drive should operate normally.