

HOME ENTERTAINMENT SOUND SYSTEMS

Features & Specifications Chart

	SA-VA1	SA-VA3	SA-VA15	SA-VA55
Number of Amplifiers	5	7	5	8
Number of Speaker Drive Units	8	10	8	8
Front Power Output	22 watts x 2	22.5 watts x 2	N/A	N/A
...into ohms	4 ohms	4 ohms	N/A	N/A
...at Hz to Hz, at 10% THD	10,000 Hz	10,000 Hz	N/A	N/A
Subwoofer Power Output	22 watts x 1	27 watts x 1	N/A	N/A
...into ohms at 40 Hz, 10% THD	2 ohms	2 ohms	N/A	N/A
Center Power Output	17 watts x 1	26 watts x 1 tweeter; 25 watts x 2 midrange	N/A	N/A
...into ohms	4 ohms	4 ohms	N/A	N/A
...at Hz, at 10% THD	10,000 Hz	10,000 Hz tweeter; 1,000 Hz midrange	N/A	N/A
Surround Power Output	17 watts x 1	26 watts x 1	N/A	N/A
...into ohms at 1 kHz, 10% THD	4 ohms	4 ohms	N/A	N/A
Infrared Wireless Surround Speakers				•
Dolby® Pro Logic® Circuitry	•	•	•	•
Wireless Remote Control	•	•	•	•
Speaker Magnetic Shielding	•	•	•	•
Easy Connection to Your TV	•	•	•	•
Automatic Power On/Off	•	•	•	•
Surround Modes	3	3	3	5
Hall Mode	•	•	•	•
Theater Mode				•
Stadium Mode				•
Simulated Mode	•	•	•	•
Variable Surround Sound Delay Time	•	•	•	•
Memory Modes			3	5
Audio Line Inputs	2	2	2	2
Audio Line Outputs	2	2	2	2
Center Channel Line Output	•	•	•	•
Center Level Adjustment	•	•	•	•
Surround Level Adjustment	•	•	•	•
Subwoofer Level Adjustment	•	•	•	•
Sequential Test Tone	•	•	•	•
Bass and Treble Controls	•	•	•	•
Bass Boost Switch	•	•	•	•
Balance Control	•	•	•	•
Muting Switch	•	•	•	•
Fluorescent Display	•	•	•	•
Front Speaker Drivers, Total	4" x 2	2" x 2; 5 1/8" x 2	4" x 2	2" x 2; 5 1/8" x 2"
Subwoofer Drivers, Total	5 1/8" x 2	6 1/4" x 2	5 1/8" x 2	6 1/4" x 2
Center Speaker Drivers, Total	2" x 2	2" x 2	2" x 2	4" x 2
Surround Speakers Drivers, Total	3 1/8" x 2	4" x 2	3 1/8" x 2	4" x 2
Front Speaker Width	7"	7 7/8"	N/A	N/A
Front Speaker Height	4 1/2"	4 1/2"	N/A	N/A
Front Speaker Depth	11"	11"	N/A	N/A
Weight	77 lbs	103 lbs	N/A	N/A