

# SLV-D500P

DVD/VCR Combination



## Key Features

- Combination DVD and VCR Player
- JPEG Digital Picture Playback (CD-R/RW)
- ▲ Quickset® Timer Dial
- ▲ VCR Plus+® Programming
- ▲ Cinema Illumination Multi-Brand TV Remote Control
- Progressive Output for DVD (480P)
- DVD, DVD+RW/+R, DVD-RW/-R (Video Mode) Playback
- CD, SVCD, VCD, CD-R/RW\* & MP3 Playback

**Progressive Scan**



## Additional Features

### General Features

- Combination DVD and VCR Player
- ▲ Cinema Illumination Multi-Brand TV Remote Control\*
- Multi-Lingual On-Screen Display
- DVD Player**
- Progressive Output for DVD (480P)
- DVD, DVD+RW/+R, DVD-RW/-R (Video Mode) Playback
- ▲ JPEG Digital Picture Playback (CD-R/RW)
- CD, SVCD, VCD, CD-R/RW\* & MP3 Playback
- Virtual Surround Sound
- Frame Advance (Forward)
- Screen Zoom Function
- 10 bit/54 Mhz Video DAC
- Parental Lock
- Bookmark Function

### Video Cassette Recorder

- 4-Head Hi-Fi VHS Video Cassette Recorder
- 19 Micron Heads for Optimized EP recording
- S-VHS Quasi Playback
- ▲ Quickset® Timer Dial
- ▲ VCR Plus+® Programming
- Flash Rewind- Rewinds a T-120 Video Tape in about 60 Seconds
- Plug and Play Easy Setup for Tuner & Clock
- Auto Head Cleaner
- 1 Month/8 Event Recording Timer
- Auto Tracking for VHS Playback
- Commercial Skip
- Screen Saver

### Inputs and Outputs

- RF Output for DVD & VCR
- Component Video Output & S-Video Output for DVD
- Coaxial & Optical Digital Output for DVD
- Front A/V inputs for Camcorder or Game System
- Dolby® Digital dts® Multi-Channel Digital Audio Output

▲ = Step-Up Feature

**Preliminary and Confidential**

**SONY**

# SLV-D500P

DVD/VCR Combination

## Key Technology



### Quickset Timer Dial

You can program your VCR with just a quick turn of the wrist. Press the Quickset Timer Dial to activate the system. Turn the knob to set the date, start time, stop time, and channel.



### JPEG Digital Image Playback

View your JPEG digital images from a CD-R/RW\* right on your TV.

## Specifications

### Specifications

#### Video

- Laser Assemblies for DVD/CD: Yes (2)
- Video Horizontal Resolution: >500 TV Lines for DVD

#### Audio

- Audio Frequency Response (DVD, 96 kHz PCM): 2-44,000Hz,  $\pm 1.0$ dB
- Audio Frequency Response (DVD, 48 kHz PCM): 2-22,000Hz,  $\pm 0.5$ dB
- Audio Signal-to-Noise Ratio: > 115 dB
- Audio Dynamic Range: > 103 dB (DVD); > 99 dB (CD)
- Harmonic Distortion: <0.003%

### Connections

#### Video Inputs

- RF Video Input (VCR only) x 1
- Composite Video Input (VCR Section) x 2 (One On the Front of Unit)

#### Video Outputs

- Component Video Output (DVD Only) x 1
- S-Video Output (DVD Only) x 1
- Coaxial Digital Output (DVD Only) x 1
- Optical Digital Output (DVD Only) x 1
- RF Video Output (VCR/DVD) x 1
- Composite Video Output (DVD/VCR) x 1

#### Audio Inputs

- Audio Line Inputs (VCR) x 2 (One On the Front)

#### Audio Outputs

- Additional Analog Audio Output (DVD) x 1
- Audio Line Level Output (VCR) x 1

#### General

- Power Requirements: AC120V, 60Hz

### Accessories

#### Supplied Accessories

- Instruction Manual
- Remote Commander® Remote Control\*
- Batteries: AA x 2
- 75-Ohm Coaxial Video Cable w/F Type Connector (1)
- Audio Video Cord (RCA Type) (1)

#### Weights & Measures

- TBD

#### UPC Code

- 027242622517

©2003 Sony Electronics Inc. All rights reserved. Features and specifications are subject to change without notice. Sony, AutoClock, ChildLoc, Quickset, and WEGA are trademarks of Sony. VCR Plus+, C3, ALLSET and PlusCode are trademarks of Gemstar Development Corporation. DIRECTV is a trademark of DIRECTV, Inc., a unit of Hughes Electronics Corporation. Energy Star and the Energy Star logo are registered US marks. All other trademarks and logos are property of their respective owner.

\*CD-R/RW playback may not be compatible with all discs, depending on recording conditions.

\*\*Multi-Brand TV Remote Control is compatible with most major TV brands.